

BOOSTER AMPLIFIER

A-BA-120W/240W/480W/880W/1000W



Features:

- 70-100V constant pressure output and 4-16 Ohms output, balanced, no grounding, 2 or 4 channel of your choice
- 4 Pcs LED indicators for status display
- Protection for short-C, over heat and over load
- Series amplifiers of high output is available
- Pure Power Amplifier
- With limiter function, music without distortion



Specification:

| Model | A-BA-120W | A-BA-240W | A-BA-480W | A-BA-880W | A-BA-1000W |
|-------------------------|--------------|-----------|-----------|-----------|------------|
| Line Voltage | 70-100V | | | | |
| Impedence | 4-16Ohms | | | | |
| Rated Power | 120W | 240W | 480W | 880W | 1000W |
| Dimension | 435*390*90mm | | | | |
| Weight | 14.5 | 17.26 | 18.5 | 21 | 21.5 |
| With 100V and 0db input | | | | | |