

ZONE EXPANSION KEYPAD (12 ZONE) KP-EVAC-12Z



Description:

The KP-EVAC-12Z Zone Expansion Keypad is an extension to the EVAC-500RM Voice Alarm System Remote Microphone that adds additional zone-select keys. It has the same stable metal base as the call station. In addition to tabletop use, the special design allows it to be neatly flush-mounted in desktops.

Features:

- Each zone expansion keypad supports 12 zone selections.
- The keypad is used to expand the capacity of remote microphone for multiple-zones.
- Connecting one of these keypads to 12 zones or zone groups that can be selected.
- Up to 11 keypads can be added to an EVAC-500RM Remote Microphone.
- LEDs on the keypad indicate the active zones.
- 12 zone selection keys and 12 zone selection LEDs.
- Total system capacity of 12 zones.
- Keypad internal line will be monitored, fault will be indicated by LED and buzzer.



ZONE EXPENSION KEYPAD (12 ZONE) KP-EVAC-12Z

Specifications:

Model	KP-EVAC-12Z
Description	Zone Expansion Keypad (12 Zone)
Power Consumption	3W
Zone Capacity	12 Zones
System Capacity	11 units of keypads
Frequency Response	80Hz~16kHz
THD	<1% at RMS 1kHz
S/N Ratio	≥70dB
Operating Temperature	-20°C to +70°C
Power Supply	DC5V, ±20%
Humidity	<95% no condensation
Dimensions	132(W)×150(H)×52(D) mm
Weight	0.7kg